KH-9140CS00-ES



Highligths

- Induction hob 90cm
- 5 zones
- 4-side bevel
- 4x16cm, , 1x25cm, 2xCookBridge
- 5 Boosters (max. 3500 W)
- Multislider Control, 5 Timers
- AutoHeatControl
- Hot Surface Indicator
- Key Lock

- Stop&Go
- Key Lock





Keep your children safe from accidentally using the microwave with the easy to set up Child Lock.



The ultimate in versatility, CookBridge provides flexibility for pans of all shapes and sizes. By simply combining two induction zones you can create an extra large zone for big pots and pans.



Simple yet effective, Sharp puts the most common cooking tasks at your fingertips, allowing you to boil, fry, melt chocolate and keep your food warm at the touch of a button.



Maximum power in seconds for a speed-up heating and a cooking time reduction.



Intuitive sliding controls allow you to select the power level easily.



Freeze time when you need to. Our Stop&Go technology allows you to pause and take that all important call when cooking, then press again to continue.

Ezaugarri gehiago



Key Features

Colour Black

Construction type Built-in

Width (cm) 90

Flexible zone 2 x Bridge Zone

Control location Front

Frame -

Bevel 4 Side Bevel

Zone dimensions (mm) / Power (W)

(Boost W)

"4 x 16 cm / 1400 W (Boost 1800 W) 1 x 25 cm /

2800 W (Boost 3500 W)"

Total power (kW) 10,8

Power levels (Nbr) 9 level + Boost

Other features

Child Lock Bai

Control Type Multislider Slider Control

Dimensions and Weight

Brutto dimensions W \times H \times D (cm) 92.6 \times 14.2 \times 58.1

Net Weight (kg) 16,21

Hob dimensions W x H x D (cm) $89 \times 5.6 \times 52$

Cut-out dimensions (W x H x D) (mm)

86 x 49

Brutto weight (kg)

17,78

European Article Number

EAN Code 4550556101349

Accessories

Spatula Ez-

Functions

Stop & Go

InductionBoost Bai

AutoHeatControl Bai

Timers (Nbr) 5

InductionBoost (Nbr) 5

2xZone

3xZone

Extended2xZone

Multislider Control Bai

CookBridge Bai

SliderTouch

Bai

Timer function

Bai

EasyToClean Surface

Bai

Safety

Pan detector

Thermal cut off system

Bai

Key lock

Bai

AutoOFF

Power, Consumption and Voltage

Voltage (V) / Frequency (Hz) $220\text{-}240\text{V}\sim/380\text{-}415\text{V}~3\text{N}\sim$

Bai

47

Hob Features

Fuse rating (A)

Hob type Induction

Cooking zones (Nbr)

Hot surface indicator(hob)

