


Hobs

KH-6I38CS00-EU




Highligths

- 4-Side Bevel
- SliderTouch Control, 4 Timers
- Hot Surface Indicator
- Stop & Go
- Key Lock
- AutoHeatControl
- Induction hob - 60cm
- 4 zones
- 4x16cm, 2xCookBridge
- 4 Boosters (max. 3600 W)

SHARP
Be Original.



Keep your children safe from accidentally using the microwave with the easy to set up Child Lock.



The ultimate in versatility, CookBridge provides flexibility for pans of all shapes and sizes. By simply combining two induction zones you can create an extra large zone for big pots and pans.



Simple yet effective, Sharp puts the most common cooking tasks at your fingertips, allowing you to boil, fry, melt chocolate and keep your food warm at the touch of a button.



Effortlessly prepare all your favourite dishes with our Induction hobs, offering rapid heating, so you can heat all your pots and pans faster.



Intuitive sliding controls allow you to select the power level easily.



Freeze time when you need to. Our Stop&Go technology allows you to pause and take that all important call when cooking, then press again to continue.

More Features

SHARP
Be Original.

Key Features

Colour	Black
Construction type	Built-in
Control type	Slider
Hob type	Induction
Flexible zone	2 x CookBridge
Control location	Front
Frame	No
Bevel	4-Side Bevel
Width (cm)	60
Cooking zones (Nbr)	4
Zone dimensions (mm) / Power (W) (Boost W)	4 x 160 mm / 1400 W (Boost 1800 W); 2 x CookBridge 354 x 160 mm / 2800 W (Boost 3600 W)
Total power (kW)	7.4
Power levels (Nbr)	9

Dimensions and Weight

Brutto dimensions W x H x D (cm)	626 x 142 x 581
Net Weight (kg)	11
Hob dimensions W x H x D (cm)	590 x 56 x 520
Cut-out dimensions (W x H x D) (mm)	560 x 490

Brutto weight (kg)	12
--------------------	----

European Article Number

EAN Code	4974019143835
----------	---------------

Accessories

Main cable	Yes (1.1 m)
Spatula	Yes

Functions

AutoHeatControl	Yes
Timers (Nbr)	4
InductionBoost (Nbr)	4

Safety

Pan detector	Yes
Thermal cut off system	Yes
Hot surface indicator	Yes
Key lock	Yes
Child lock(safety)	Yes

AutoOFF

Yes

Power, Consumption and Voltage

Voltage (V) / Frequency (Hz)

220-240 V / 50 Hz

Fuse rating (A)

32

SHARP
Be Original.